

??inform?????????????. ??????AC?????mamaged AP??????, ??????, ???AC????????AP, ??????(inform)
 ???AP????AC????????(??)??, ???AP????AC???, ???(discovery)??, ?????IP????domain name??AC.

??(inform)????AC?AP??????, ???????????????????????.


Details	Users	Guests	Configuration
Overview MAC Address 00:27:22:b4:ee:df Model UniFi AP Version 2.3.9.1693 IP Address 10.2.14.10 Uptime 37m 47s # Users 0 # Guests 0			
▶ Uplink (Wire) ▶ Radio (11n/b/g)			
locate restart			

AC與AP不屬於同一網段操作.
 但是由於使用了告知(inform),
 讓AC和AP之間依然能夠正常通訊.

?????????????(discovery utility)??,?????Web GUI????, ???pending?????. ?????, AC?AP?????????. ??????:

AC: 10.2.14.11/24; AP: 10.2.14.10/24; netmask: 255.255.255.0

?????????, AC?AP????????, ?????????AP???, ?????:



??manage???AP??????AC????, ?????:



???, ??URL??unifi:8080, ????, ?????10.2.14.100:8080?gateway, ???DNAT?????AC???. ????, ??????????????. ?? Apply??, ???adopting???, ????????

Ubiquiti UniFi - Discovery Utility				
Discovering UniFi access points ...				
MAC Address	IP Address	Model	Version	Status
00:27:22:b4:ee:df (UBNT)	10.2.14.10 (dhcp)	UniFi AP	2.3.9.1693	Adopting
				locate manage rese

??DNAT?????, ???FGT?VIP?????, ?????:

Name	port14\$10.2.13.200@UNIFI8080		
Comments	<input type="text" value="Write a comment..."/> 0/255		
Color	[Change]		
External Interface	port14 (10.2.14.0/24;service)		
Type	Static NAT		
<input type="checkbox"/> Source Address Filter	<input type="text"/> (e.g.:		
External IP Address/Range	10.2.14.100	- 10.2.14.100	
Mapped IP Address/Range	10.2.13.200	- 10.2.13.200	
<input checked="" type="checkbox"/> Port Forwarding			
Protocol	<input checked="" type="radio"/> TCP	<input type="radio"/> UDP	<input type="radio"/> SCTP
External Service Port	8080	- 8080	
Map to Port	8080	- 8080	

?????????(policy binding), ?????AC????:

Policy Type	<input checked="" type="radio"/> Firewall <input type="radio"/> VPN
Policy Subtype	<input checked="" type="radio"/> Address <input type="radio"/> User Identity <input type="radio"/> Device Identity
Incoming Interface	port14 (10.2.14.0/24;service)
Source Address	<input type="text"/> port14:10.2.14.0/24
Outgoing Interface	port13 (10.2.13.0/24;mgmt)
Destination Address	<input type="text"/> port14\$10.2.13.200@UNIFI8080
Schedule	always
Service	ALL
Action	<input checked="" type="checkbox"/> ACCEPT
<input type="checkbox"/> Enable NAT	
<input type="checkbox"/> Log Allowed Traffic	

UTM Security Profiles

<input type="button" value="OFF"/> AntiVirus	<input type="text" value="default"/>
<input type="button" value="OFF"/> Web Filter	<input type="text" value="default"/>
<input type="button" value="OFF"/> Application Control	<input type="text" value="default"/>
<input type="button" value="OFF"/> IPS	<input type="text" value="default"/>
<input type="button" value="OFF"/> Email Filter	<input type="text" value="default"/>
<input type="button" value="OFF"/> SSL/SSH Inspection	<input type="text" value="default"/>

Traffic Shaping

?????, ??1~2????, ??AC?Web GUI??. ??????, adopting???, AP?LED?????????????????. ?????????????????AP??????AC.

Welcome admin | [settings](#) | [logout](#)

Access Points: **1** connected | 0 disconnected | 0 pending

MAC: 00:27:22:b4:ee:df

Connected

Details	Users	Guests	Configuration														
Overview <table border="1"> <tr> <td>MAC Address</td> <td>00:27:22:b4:ee:df</td> </tr> <tr> <td>Model</td> <td>UniFi AP</td> </tr> <tr> <td>Version</td> <td>2.3.9.1693</td> </tr> <tr> <td>IP Address</td> <td>10.2.14.10</td> </tr> <tr> <td>Uptime</td> <td>26m 17s</td> </tr> <tr> <td># Users</td> <td>0</td> </tr> <tr> <td># Guests</td> <td>0</td> </tr> </table>				MAC Address	00:27:22:b4:ee:df	Model	UniFi AP	Version	2.3.9.1693	IP Address	10.2.14.10	Uptime	26m 17s	# Users	0	# Guests	0
MAC Address	00:27:22:b4:ee:df																
Model	UniFi AP																
Version	2.3.9.1693																
IP Address	10.2.14.10																
Uptime	26m 17s																
# Users	0																
# Guests	0																
Uplink (Wire) Radio (11n/b/g)																	
locate restart																	

?????????, ?????AC?????????, ??????????.

**?????FortiGate?NPU??, ?Unifi AP????frame???ASIC-based?NP(Network Processor) unit?handle??
A: ??????. ??Session Monitor????Unifi AP????traffic????NPU????, ??????I/O??????????.

Top Session by Forward Traffic								
#	Src	Dst	Policy ID	Device	Application Name	Bytes (Sent/Received)	FortiASIC	Actions
1	10.3.100.200:57540	1.173.235.65:9612	34	N/A	N/A	326 ↓	NP2	
2	10.2.14.12:41168	74.125.31.188:5228	30	android-c97ab1d6f4fe214c	N/A	512 ↓	NP2	
3	10.2.14.12:53933	61.147.113.82:80	30	android-c97ab1d6f4fe214c	N/A	665 ↓	NP2	
4	10.3.100.200:56999	114.42.43.140:27282	34	N/A	N/A	3,236 ↓	NP2	
5	10.2.14.12:53979	61.147.113.82:80	30	android-c97ab1d6f4fe214c	N/A	6,623 ↓	NP2	
6	10.2.14.12:53977	61.147.113.82:80	30	android-c97ab1d6f4fe214c	N/A	2,168 ↓	NP2	
7	10.2.14.12:53981	61.147.113.82:80	30	android-c97ab1d6f4fe214c	N/A	1,009 ↓	NP2	
8	10.2.14.12:54175	69.171.237.24:443	30	android-c97ab1d6f4fe214c	N/A	512 ↓	NP2	
9	10.2.14.12:40660	74.125.31.106:443	30	android-c97ab1d6f4fe214c	N/A	485 ↓	NP2	
10	10.2.14.12:40012	202.112.29.82:123	30	android-c97ab1d6f4fe214c	N/A	152 ↓	-	
11	10.2.13.200:58323	119.235.235.91:443	36	WIN-M6V0GQEFQ09	N/A	136 ↓	NP2	
12	10.2.14.12:52386	119.235.235.110:9418	30	android-c97ab1d6f4fe214c	N/A	456 ↓	NP2	