

??

??? SIP gateway ?? '2100'????? 4 ? port?????? dialer ??????????

1. ?????? port ?????????????? 300 ?(1800 ??)
2. ????????????????????????????????????? 503 SIP ???
3. ?????????? port?

????

1. FreePBX Distro 1.810.210
2. Asterisk 1.8.10
3. FreePBX 2.10

??

extensions_custom.conf?

```
[LB-trunk_all-v3]
exten => _X.,1,Set(TRUNK_NAME=LBtrunk)
exten => _X.,n,Noop(Load Balancing for Trunk ${TRUNK_NAME})
exten => _X.,n,AGI(check_LB_ports.php,${TRUNK_NAME},${EXTEN})
exten => _X.,n,Hangup(42)
```

?? Outbound Trunk

FreePBX Admin > Trunks

- Trunk Name = LB-2100
- Custom Dial String = Local/\$OUTNUM\$@LB-trunk_all-v3/n

AGI: check_LB_ports.conf.php

reference to undefined name 'syntax' Exception of type 'MindTouch.Deki.Script.Runtime.DekiScriptUndefinedNameException' was thrown. (click for details)

AGI: check_LB_ports.php

AGI Dial Command: exec_dial(SIP/LBtrunk_9/LBtrunk_9_6243531,300,L(261000:61000:30000))

261000: ??????? ms
61000: ??????????? ms
30000: ??????? ms

?????????????
L(261000::) ???????

reference to undefined name 'syntax' Exception of type

'MindTouch.Deki.Script.Runtime.DekiScriptUndefinedNameException' was thrown. ([click for details](#))