



???? Raspberry Pi ??????????????????

1. ?? pre-installed ????
2. ?????? MicroSD ?

?????????

?????<http://www.raspberrypi.org/downloads/>

?????? MicroSD ?

Windows??? [Win32DiskImager](#) ???????

Linux?

dd bs=4M if=2015-02-16-raspbian-wheezy.img of=/dev/sdd

NOTE: ?? /dev/sdd ??? MicroSD ??

????

??? 2018/9/1

? 2016 Novemer Release ?????????? SSH ????????????????

?????????????/???

1. Launch Raspberry Pi Configuration from the Preferences menu
2. Navigate to the Interfaces tab
3. Select Enabled next to SSH
4. Click OK

?????? headless Raspberry Pi

????? Linux ??? Micro SD ?????????? boot ?????????????????????? ssh?????????????????Raspbian ??????????????????????
??? SSH ???

SSH ??????pi / raspberry

????????????????????????????? raspi-config?

????

?? raspi-config ??????????????????????????????????????

sudo raspi-config

Raspberry Pi Software Configuration Tool (raspi-config)

Setup Options

- 1 Expand Filesystem Ensures that all of the SD card storage is available to the OS
- 2 Change User Password Change password for the default user (pi)
- 3 Enable Boot to Desktop/Scratch Choose whether to boot into a desktop environment, Scratch, or the command line
- 4 Internationalisation Options Set up language and regional settings to match your location
- 5 Enable Camera Enable this Pi to work with the Raspberry Pi Camera
- 6 Add to Rastrack Add this Pi to the online Raspberry Pi Map (Rastrack)
- 7 Overclock Configure overclocking for your Pi
- 8 Advanced Options Configure advanced settings
- 9 About `raspi-config` Information about this configuration tool

<Select>

<Finish>

??????

????????????? 3GB ??????????????

\$> sudo raspi-config

?? 1. Expend Filesystem

???????