



???????

Asus WL-HDD ??????????USB ?????.

??Firmware

- ??? [koppel](http://koppel.cz/cdmawifi/download/1...9-USB-1.70.trx) firmware
- ??Web ?Asus ??????????
- ?????USB 3.5G E220 ???

????firmware

?? usb to serial port birdge chipset ? usb vender id (VID)and product id (PID) ?ftdi*.h ??? ????? 3G ????? support

?????

1.asus offical source:

http://files.wl500g.info/asus/wl500g/gpl/GPL_1927.zip

2.oleg patch source:

<http://oleg.wl500g.info/1.9.2.7-8/wl...2.7-8.tar.bz2>

3.koppel patch source:

<http://koppel.cz/cdmawifi/download/1...SB-1.68.tar.gz>

???????

4. oleg's toolchain for oleg's patch:

<http://oleg.wl500g.info/uClibc-0.9.1...3-full.tar.bz2>

??????

4.ubuntu 7.10 x86

5. ?apt-get install?????package

patch //for patch

libc6-dev, build-essential, flex, gawk //for compile

libncurses5-dev //for make kernel

zlibg-dev //for LZMA_Lib

6. ?GPL_1927.zip???/root

cd /root; tar xf GPL_1927.zip

7. ??toolchain

cd /; ln -s /root/broadcom/opt /opt;

cp /root/hndtools-mipsel-uclibc-3.2.3-full.tar.bz2 /; tar xf hndtools-mipsel-uclibc-3.2.3-full.tar.bz2

8. ??toolchain PATH

cd; joe .bashrc;

??????:

export PATH=\$PATH:/opt/brcm/hndtools-mipsel-linux/bin:/opt/brcm/hndtools-mipsel-uclibc/bin

?????root??

patch oleg's patch

9. ??????

cd /root/boardcom/src; mkdir gateway;

10. patch

tar xf wl500g-1.9.2.7-8.tar.bz2;

cd wl500g-1.9.2.7-8;

make kernel; make;

patch koppel's patch

11. patch

cd /root/boardcom/src;

tar xf usb-1.9.2.7-8-USB-1.68.tar.gz;

cd cdma;

make;

???????

```
compile everything  
12.compile  
cd /root/boardcom/src/gateway;  
make;
```

```
?????????, ???firmware?????:  
/root/broadcom/src/gateway/mipsel-uclibc/WLHDD-1.9.2.7-8-USB-1.68.trx  
????firmware???web???recovery????WLHDD
```

???

PCZONE:<http://www.pczone.com.tw/vbb3/thread/16/139626/>

????:<http://digiland.tw/>

Oleg firmware <http://oleg.wl500g.info/>