



????? <http://benjr.tw/?q=node/505#comment-184>

????? iSCSI ?????? Intel ?? Intel® iSCSI Remote Boot ?? ROM ??? iSCSI Boot ??? ?????? Intel ??????????????

????? iSCSI ????.??? <http://support.intel.com/support/network/iscsi/remoteboot/> ???.

?????? Intel® iSCSI Remote Boot ????,?????Intel PCI-Express Server ??? Gigabit family ??????.?????????????

??????.

- Intel® Gigabit CT Desktop Adapter(**Controller:82574L**)
- Intel® Gigabit ET Dual Port Server Adapter(**Controller:82576**)
- Intel® Gigabit EF Dual Port Server Adapter(**Controller:82576**)
- Intel® Gigabit ET Quad Port Server Adapter(**Controller:82576**)
- Intel® PRO/1000 PT Quad Port Server Adapter(**Controller:82571EB**)
- Intel® PRO/1000 PT Quad Port LP Server Adapter(**Controller:82571EB**)
- Intel® PRO/1000 PF Quad Port Server Adapter(**Controller:82571EB**)
- Intel® PRO/1000 PT Dual Port Server Adapter(**Controller:82571EB**)
- Intel® PRO/1000 PF Dual Port Server Adapter(**Controller:82571EB**)
- Intel® PRO/1000 PT Server Adapter(**Controller:82572EI**)
- Intel® PRO/1000 PF Server Adapter(**Controller:82572EI**)
- Intel® Gigabit PT Quad Port Server ExpressModule(**Controller:82571**)
- Intel® 10 Gigabit AF DA Dual Port Server Adapter(**Controller:82598EB**)
- Intel® 10 Gigabit AT Server Adapter(**Controller:82598EB**)
- Intel® 10 Gigabit XF SR Server Adapter(**Controller:82598EB**)
- Intel® 10 Gigabit XF LR Server Adapter(**Controller:82598EB**)
- Intel® 10 Gigabit XF SR Dual Port Server Adapter(**Controller:82598EB**)
- Intel® 10 Gigabit CX4 Dual Port Server Adapter(**Controller:82598EB**)

????????? iSCSI Remote Boot ? driver,?????????????????????.

- Microsoft\* Windows\* Server 2003 SP1, SP2, R2 x86
- Microsoft Windows Server 2008 x86
- Red Hat\* Enterprise Linux 4 U3, Red Hat\* Enterprise Linux 5
- Novell SUSE\* Linux Enterprise 9 SP3, Novell SUSE\* Linux Enterprise 10

### **?? iSCSI Remote Boot ROM:**

Intel ?????? Intel iSCSI Network Adapter Boot Configuration Utility (iSCSIUtil) ??? DOS ???,????????? DOS  
 ??? Intel NIC firmware ? iSCSI Remote Boot ROM.????????????????? iSCSIUtil\ DOS\iscsiutil.exe ??? Intel  
 NIC ? iSCSI Remote Boot ROM ????.?????????:  
 iSCSIUtil -[OPTION] or -[OPTION]=[VALUE]

```
C:\iscsiutil -all -up
Intel(R) iSCSI Boot Utility
iSCSIUtil version 2.3.17.00
Copyright (C) 2003-2009 Intel Corporateion
```

Programming flash on part 1 with iSCSI Boot image  
 An Intel(R) Boot Agent setting has been detected on this device. Programming

this device with Intel(R) iSCSI Boot will erase this setting.

Would you like to continue? **(Y)es or (N)o:****Y**

\*

Flash update successful.

Flash not enabled on port 2

Use the "-FLASHENABLE" parameter to enable to flash

Port	Network Address Series	WOL	Boot ROM Type	Version
1	001517785DD6	Gigabit YES	iSCSI Enabled	<b>2.3.17</b>
2.	001517785DD7	Gigabit N/A	FLASH Disabled	2.3.17

???????????? pre-installed Intel Boot Agent image ???,?????????????????.???????????? Y(yes) ???????,???????

????????????????.

ISCSIUTL -NIC=1 -FLASHENABLE

???????????? Intel ??? Option ROM ????.

Intel(R) iSCSI Boot version 2.3.17  
 Copyright (c) 2003-2009 Intel Corporation. All rights reserved.  
 Press ESC key to skip iSCSI boot initialization.  
 Press <Ctrl-D> to run setup...

?? <Ctrl-D> ???? Intel iSCSI Remote Boot ? Option ROM.?? iSCSI initiator ???.

### **?? iSCSI Remote Boot**

???????????? Intel ? Option ROM ??? iSCSI Target ??? Lun ,????????? iSCSI Target ?????,????? RHEL5 ? iSCSI Target ??? [RHEL5 - iSCSI IP-SAN](#) ??? Intel iSCSI Remote Boot ? option ROM.

?? iSCSI Remote Boot Port Selection Menu ??????????? Intel iSCSI Remote Boot-capable adapters.????????  
?? Intel ?? PCI device ID, PCI bus/device/function ?? MAC Address

?????????? 10 iSCSI Remote Boot-capable ports ,??????????,???? Server ??? 10 ?????????????? iSCSI  
Remote Boot status ,????????? BOOT:PRIMARY, BOOT:SECONDARY

Boot ??????????.

- **Primary:**

?????? Primary(? 'P' ??????? Primary) Intel iSCSI Remote Boot ?????? iSCSI Target ???????????.????  
?????????? Primary.

- **secondary:**

?????? secondary(? 'S' ??????? secondary) , ??? Primary ????? secondary ??? iSCSI Target ????.??  
????????????? secondary.

- ? 'D' ??? iSCSI Remote Boot ??????????.
- ? 'B' ??????? LED ??.
- ? 'ESC' ??????.

???? iSCSI Boot ROM ???????????,????????????? PRIMARY ???? SECONDARY.

?????????? iSCSI setup menu ??????:

- **iSCSI Remote Boot Configuration**  
?????? iSCSI Remote Boot initiator ? target ?????? IP ,name ?? Boot Lun ??????.
- **CHAP Configuration**  
?? iSCSI ??? CHAP(Challenge Handshake Authentication Protocol) ??????,?????? MD5 ????????.????????????????????.
- **Discard Changes and Exit**  
????? iSCSI Remote Boot Configuration ?? CHAP Configuration ??????"Discard Changes and Exit" ? ??????????????.?????? "iSCSI Remote Boot Port Selection Menu
- **Save Changes and Exit**  
?? "Save Changes and Exit" ?????? iSCSI Remote Boot Configuration ?? CHAP Configuration ?????? ??,???????"iSCSI Remote Boot Port Selection Menu

?????? "SCSI Boot Configuration"

?????? "Initiator" ? "Target" ?,????????? "Intel iSCSI Remote Boot" ??? "Initiator" ????.

- **Use Dynamic IP Configuration (DHCP)**

??? DHCP ??? iSCSI ?????????? DHCP ?? client IP address, subnet mask, and gateway IP address.

- **Initiator Name**

????? iSCSI initiator name ?????? iSCSI target ??? Intel iSCSI Remote Boot ???.

- **Initiator IP**

????? IP ? IP ??? Target ??????? Target ???.

- **Subnet Mask**

IP ? subnet-mask ?????? IP ???.

- **Gateway IP**

?? Target ? Initiator ??????? gateway ????.

????? Target ???,?? Target Name(?? IQN) ??????????,?? iSCSI Target ?? IP.

- **Use DHCP for iSCSI Target Information**

??? DHCP ??? iSCSI ?????????? DHCP ?? iSCSI target's IP address, IP port number, iSCSI target name, and SCSI LUN ID.

- **Target Name**

Target ?? IQN (iSCSI Qualified Name)???? iqn.yyyy-mm.<reversed domain name>[:identifier] .

- **Target IP**

iSCSI Target ?? IP ??.

- **Target Port**

iSCSI ???? TCP Port Number(?? 3260).

- **Boot LUN**

? SCSI RAID ???? SCSI HD ??????????(LUN),SCSI ??????????????????,,? LUN ?? 0 ??? RHEL5 ? iSCSI Target ? lun0 ????????? controller device.

iSCSI ?? CHAP-Challenge Handshake Authentication Protocol(? MD5 ?????????),?????. ?? CHAP ??:??????,?? ?? Target ????.

- **User Name**

iSCSI target ????? CHAP ????.

- **Target Secret**

iSCSI target ????? CHAP ???. ?????? Initiator Secret ??????????.

- **Use Mutual CHAP**

?(Mutual) CHAP ??,??????,?? Target ???? Initiator ????????

- **Initiator Secret**

iSCSI Initiator Mutual CHAP ?? ?????? Target Secret ??????????

????????????????????????? iSCSI ? drive.

```
Intel(R) iSCSI Boot version 2.3.17
Copyright (c) 2003-2009 Intel Corporation. All rights reserved.
Press ESC key to skip iSCSI boot initialization.
Initializing adapter configuration - MAC address(001517785DD6).
Using STATIC configuration for primary port, please wait.
iSCSI Target Name    : iqn.2009-4.bios:storage
iSCSI Target IP Address : 192.8.1.1
LUN ID: 1          Port: 3260
iSCSI Initiator IP   : 192.8.1.24
iSCSI Gateway IP    : 192.8.1.1
iSCSI Initiator Name : iqn.ben

Attempting to connect to target disk using MAC address(001517785DD6)
LUN: 1 DEVICE: IET VIRTUAL-DISK 18.63 GB
```

BIOS Boot Menu

??? Intel iSCSI Remote Boot ?? BIOS ? Boot Menu ???? Intel® iSCSI Remote Boot ??? ??????? IBM ? Server ?
??? Boot Menu ??????????.

