

????? C?? H ?? S?? .?????LBA??
?????,?????????
????????????????(Glist and Plist) ??? CHS ,?????????LBA ??
?????LBA??,???,????Sector,?????????

????????,Seagate 7200.11,12 ,14 ??????????????.?????????0
????????? ?????? ??SMART ??????????????????????

- ????????:
1. ?????? ??, LBA? ?0 ATA????? ?
 - 2..????? ??, LBA? , ATA ?????
 ????????

Rst 0x10M
 LED:000000CC FAddr:0025BF67
 Ctrl + Z
 F3 T>
 LED:000000CC FAddr:0025BF67
 your drive is busy!

?????????
????????? ??? ??????????????

- 1.????? ??????
- ?????F?,??7200.11 ?????T?
- ?????????PCB??? ??????????

?????????Ctrl-Z

T???
??2 ? ?Z ???????

F3 T>/2
 F3 2>Z
 ?????????

?PCB??HDA?

F3 2>U
??????

- 2.F3 2>/
 F3 T>
 F3 T>i5,1,22

??G list ,?????????

3.?????????

F3 T>/1

F3 1>N1

??Smart ,??????

4. F3 1>/

F3 T>m0,2,2,0,0,0,0,22 Enter

???????

=m0,6,2,,,,,22

??1x??

????

????

?????????

m0,0,8,,,,,22

m0,8,2,,,,,22

m0,8,3,,,,,22 (??)

m0,5,1,3,5,,,22

??????