

- 前進
- 左轉
- 右轉
- 後退
- 舵機向上
- 舵機向下



????(Arduino)???Serial ?? ,?TCP /IP ??..
 ????? Lan Shield ?????????? ??????????????..
 ??FW171-3G (TP-WR703N) ??? ??? ??????????openwrt fw ,usb ???USB CAM or sound
 ?????? ?? ,web ???cgi,Java script ,php ,python?

Client ??TCP /IP ??mips FW171-3G ??, ????????? MCU?????
 ???

WEB UI ?? Arduino ??..??
 Serial port UPS??.
 ??? ???
 IP CAM
 Arduino to ??? ????.
 ?????

????Lua ?????? ??????????web ??..

??? ??????????????OSSLAB FW ??????

???? Lua code ?????? --

```
vi /www/cgi-bin/web2ser --??????
```

```
#!/usr/bin/lua
```

```
io.output("/dev/ttyUSB0") -- ?????? ???serial port ,dev ???? ??ser2net??.
```

```
io.write(os.getenv("QUERY_STRING"))
```

```
??
```

```
chmod /www/cgi-bin/web2ser 777 --????
```

```
??????????
```

```
vi /www/test.html
```

```
????javascript ?????? ?? ?? ? ? icon ?? serial ?????? 1 2 4 3
```

```
????ip stream video
```

```
<div style="float:left">
```

```
<script>
```

```
function sendSer(value){
```

```
document.getElementById("ser").src="/cgi-bin/web2ser?" +value;
```

```
}
```

```
</script>
```

```
<table>
```

```
<tr><td/><img id="ser" width="1" height="1">
```

```
<td><input type="button" onmousedown="sendSer('1')" onmouseup="sendSer('0')" value="??"  
/></td><td/></tr>
```

```
<tr><td><input type="button" onmousedown="sendSer('2')" onmouseup="sendSer('0')" value="??"  
/></td><td/>
```

```
<td><input type="button" onmousedown="sendSer('4')" onmouseup="sendSer('0')" value="??"  
></td></tr>
```

```
<tr><td/><td><input type="button" onmousedown="sendSer('3')" onmouseup="sendSer('0')" value="??"  
></td></tr>
```

```
<tr><td colspan="3" align="middle"> <input type="button" onclick="sendSer('5')" value="????"  
></td></tr>
```

```
<tr><td colspan="3" align="middle"> <input type="button" onclick="sendSer('6')" value="????"  
></td></tr>
```

```
</table>
```

```
</div>
```

```
<div style="float:left">
```

```
<iframe width="640" height="480" src="http://localhost:8080/?action=stream"/> #IP CAM steam frame
```

```
</div>
```

???? (like arduino) ??????? ?????????? ??? PWM ?????? ???????...

??

<http://hi.baidu.com/lancerz001/item/...6aaae451fd8765>

<http://hi.baidu.com/szqkfsskk/item/9...6d6ed5d1f8cdcd>

http://v.youku.com/v_show/id_XMzk0MDY0Nzcy.html