

Q: ????????????????? SDHC ????

Ans:

1. ????????? SDHC ???USB ? SDHC ???
2. ??? [SD Formatter](#)??? SDHC ?????FAT32?  
?????? Windows ????????
3. ? NextPBX ????
4. ? USB ????? SDHC ??? NextPBX ??
5. ? telnet ?? NextPBX???????

```
mkdir /mnt/sdcard
mount -tvfat /dev/sdb1 /mnt/usb
```

```
???? //etc/init.d/asterisk.sh
??????? /mnt/usb/.... ?? /mnt/sdcard/...?
```

```
...
[ ! -d /mnt/usb/asterisk_log ] && mkdir /mnt/usb/asterisk_log
[ ! -d /mnt/usb/asterisk_log/cdr-csv ] && mkdir /mnt/usb/asterisk_log/cdr-csv
[ ! -d /mnt/usb/asterisk_gui_backups ] && mkdir /mnt/usb/asterisk_gui_backups
[ ! -d /mnt/usb/asterisk_voicemail ] && mkdir /mnt/usb/asterisk_voicemail
[ ! -d /mnt/usb/asterisk_sounds_tw ] && mkdir /mnt/usb/asterisk_sounds_tw
[ ! -d /mnt/usb/asterisk_monitor ] && mkdir /mnt/usb/asterisk_monitor
[ ! -d /mnt/usb/asterisk_moh ] && mkdir /mnt/usb/asterisk_moh
[ ! -d /mnt/usb/asterisk_record ] && mkdir /mnt/usb/asterisk_record
```

```
...
???? /root/run_a18.sh
```

```
...
#mount -t vfat /dev/sda5 /mnt/usb
#mount /dev/sda2 /mnt/usbdisk
mount /dev/sda3 /mnt/usb
mount -tvfat /dev/sdb1 /mnt/sdcard <=== ?????
```

```
????
```

```
sync;sync;sync
reboot
```

```
?????
```

```
???????? SDHC ?????????????????
```

1. ??? //etc/init.d/asterisk.sh  
??????? /mnt/**sdcard**/.... ?? /mnt/**usb**/...?

```

...
[ !-d /mnt/usb/asterisk_log ] && mkdir /mnt/usb/asterisk_log
[ !-d /mnt/usb/asterisk_log/cdr-csv ] && mkdir /mnt/usb/asterisk_log/cdr-csv
[ !-d /mnt/usb/asterisk_gui_backups ] && mkdir /mnt/usb/asterisk_gui_backups
[ !-d /mnt/usb/asterisk_voicemail ] && mkdir /mnt/usb/asterisk_voicemail
[ !-d /mnt/usb/asterisk_sounds_tw ] && mkdir /mnt/usb/asterisk_sounds_tw
[ !-d /mnt/usb/asterisk_monitor ] && mkdir /mnt/usb/asterisk_monitor
[ !-d /mnt/usb/asterisk_moh ] && mkdir /mnt/usb/asterisk_moh
[ !-d /mnt/usb/asterisk_record ] && mkdir /mnt/usb/asterisk_record

```

...

2. ??? /root/run\_a18.sh

...

```

#mount -t vfat /dev/sda5 /mnt/usb
#mount /dev/sda2 /mnt/usbdisk
mount /dev/sda3 /mnt/usb
mount -tvfat /dev/sdb1 /mnt/sdcard <=== ???

```

3. ???

```

sync;sync;sync
reboot

```

???

- ?????????????????? NextPBX ???????? SDHC ??? NextPBX ????????
- ??? SDHC ?????????????????? NextPBX ???