



Q: ?????????????????????? SDHC ????

Ans:

1. ?????????? SDHC ???USB ? SDHC ???
2. ??? SD Formatter??? SDHC ??????FAT32?  
?????? Windows ????????
3. ? NextPBX ???
4. ? USB ?????? SDHC ??? NextPBX ??
5. ? telnet ?? NextPBX???????

```
mkdir /mnt/sdcard
mount -t vfat /dev/sdb1 /mnt/usb
```

```
???? //etc/init.d/asterisk.sh
?????? /mnt/usb/.... ?? /mnt/sdcard/...?
```

...

```
[ ! -d /mnt/usb/asterisk_log ] && mkdir /mnt/usb/asterisk_log
[ ! -d /mnt/usb/asterisk_log/cdr-csv ] && mkdir /mnt/usb/asterisk_log/cdr-csv
[ ! -d /mnt/usb/asterisk_gui_backups ] && mkdir /mnt/usb/asterisk_gui_backups
[ ! -d /mnt/usb/asterisk_voicemail ] && mkdir /mnt/usb/asterisk_voicemail
[ ! -d /mnt/usb/asterisk_sounds_tw ] && mkdir /mnt/usb/asterisk_sounds_tw
[ ! -d /mnt/usb/asterisk_monitor ] && mkdir /mnt/usb/asterisk_monitor
[ ! -d /mnt/usb/asterisk_moh ] && mkdir /mnt/usb/asterisk_moh
[ ! -d /mnt/usb/asterisk_record ] && mkdir /mnt/usb/asterisk_record
```

...

```
???? /root/run_a18.sh
```

...

```
#mount -t vfat /dev/sda5 /mnt/usb
#mount /dev/sda2 /mnt/usbdisk
mount /dev/sda3 /mnt/usb
mount -t vfat /dev/sdb1 /mnt/sdcard <== ?????
```

????

```
sync;sync;sync
reboot
```

????

???????? SDHC ??????????????????

1. ????? //etc/init.d/asterisk.sh  
?????? /mnt/sdcard/.... ??? /mnt/usb/...?

...  
[ ! -d /mnt/usb/asterisk\_log ] && mkdir /mnt/usb/asterisk\_log  
[ ! -d /mnt/usb/asterisk\_log/cdr-csv ] && mkdir /mnt/usb/asterisk\_log/cdr-csv  
[ ! -d /mnt/usb/asterisk\_gui\_backups ] && mkdir /mnt/usb/asterisk\_gui\_backups  
[ ! -d /mnt/usb/asterisk\_voicemail ] && mkdir /mnt/usb/asterisk\_voicemail  
[ ! -d /mnt/usb/asterisk\_sounds\_tw ] && mkdir /mnt/usb/asterisk\_sounds\_tw  
[ ! -d /mnt/usb/asterisk\_monitor ] && mkdir /mnt/usb/asterisk\_monitor  
[ ! -d /mnt/usb/asterisk\_moh ] && mkdir /mnt/usb/asterisk\_moh  
[ ! -d /mnt/usb/asterisk\_record ] && mkdir /mnt/usb/asterisk\_record

...

2. ???? /root/run\_a18.sh

...  
#mount -t vfat /dev/sda5 /mnt/usb  
#mount /dev/sda2 /mnt/usbdisk  
mount /dev/sda3 /mnt/usb  
mount -tvfat /dev/sdb1 /mnt/sdcard <== ?????

3. ?????

sync;sync;sync  
reboot

????

- ?????????????????? NextPBX ??????? SDHC ??? NextPBX ????????
- ??? SDHC ?????????????????? NextPBX ???