

????????

??A?????B?????B?????????A??A????????????????????????????????????B????????
 ??????A???? A ?????????????????????B????????????????A????????????

?? Asterisk ????????????????? feature??????IP????????????????????????????????
 ??????????Asterisk?

???

- 2009-04-30 ??extensions.conf ????"????????????????5" ?????????????????????
- 2009-04-30 ?????????????????????

?????

? A ??? B ?
 A?? -> B?(??) -> A ????????????????????? 5 -> A ?? 5 -> A ????????????????????? -> A ????(???)

? B ?????
 ??????? A?? -> A ??? -> ?????? B?? -> B ?????? A ??

????

- ????????????????? Voicemail ? FollowMe?
- ??????? extensions.conf ?????????? FreePBX ?????????????????????????????

???

????	????	??
/etc/asterisk	extensions.conf	???(??)
/etc/asterisk	extensions_custom.conf	???(??)
/var/lib/asterisk/agi-bin	busy_callback.sh	AGI(??)
/var/lib/asterisk/sounds	busy-callback.gsm (??? 2009-4-30)	???(??)
/var/lib/asterisk/sounds	busy-callback-ok.gsm (??? 2009-4-30)	???(??)

/etc/asterisk/extensions.conf
 ?????????????????????

```

; Extensions with no Voicemail box reporting BUSY come here
;exten => s-BUSY,1,NoOp(Extension is reporting BUSY and not passing to Voicemail)
;exten => s-BUSY,n,Playtones(busy)
;exten => s-BUSY,n,Busy(20)
    
```

; The following is written by A.Lang
 exten => s-BUSY,1,NoOp(Extension is reporting BUSY and set automatical CallBack)

```

exten => s-BUSY,2,ChanIsAvail(SIP/${MACRO_EXTEN}|s)
exten => s-BUSY,3,GotoIf("${AVAILSTATUS}"<="1")?s-NOANSWER,1)
exten => s-BUSY,4,Read(digit|busy-callback|1|i|3) ;Playback "busy-callback" before press digits and 3
attempts will be made.
exten => s-BUSY,5,GotoIf("${digit}"="5")?s-busy-callback,1 ;press 5 enable CallBack
exten => s-BUSY,6,Hangup

```

```

exten => s-busy-callback,1,AGI(busy_callback.sh,${CALLERID(number)},{MACRO_EXTEN})
exten => s-busy-callback,2,Playback(busy-callback-ok)
exten => s-busy-callback,3,Hangup

```

/etc/asterisk/extensions_custom.conf

```

[custom-auto-redial]
exten => _rdXXXXXX,1,NoOp(Rediald Call)
exten => _rdXXXXXX,2,Set(FROM=${EXTEN:2:3})
exten => _rdXXXXXX,3,Set(TO=${EXTEN:5:3})
exten => _rdXXXXXX,4,ChanIsAvail(SIP/${TO}|s)
exten => _rdXXXXXX,5,GotoIf("${AVAILSTATUS}" <= "1")?6:end)
exten => _rdXXXXXX,6,Set(CALLERID(all)="ReDial ${TO} <${TO}>")
exten => _rdXXXXXX,7,Dial(SIP/${FROM}|10)
exten => h,n(end),Hanghup

```

```

* ??????3????????????4????????????
_rdXXXXXX --> _rdXXXXXXXXX
Set(FROM=${EXTEN:2:3}) --> Set(FROM=${EXTEN:3:4})
Set(TO=${EXTEN:5:3}) --> Set(TO=${EXTEN:7:4})

```

/var/lib/asterisk/agi-bin/busy_callback.sh

reference to undefined name 'syntax' Exception of type
'MindTouch.Deki.Script.Runtime.DekiScriptUndefinedNameException' was thrown. (click for details)
????????????

```

#>chmod 755 busy_callback.sh

;MR=18,RT=10 ?10????????????18?

???
```

- <http://www.voip-info.org/wiki/view/A...tips+Call+Back>